

B450, Tantalum, MnO2 Tantalum, 470 uF, 20%, 4 V, SMD, Molded, Low ESR, Surge Robust, 60 mOhms, 7343, Height Max = 4.4mm



| General Information |  |
|---------------------|--|
| Supplier:           | KEMET  |
| Series:             | B450   |
| Dielectric:         | MnO2 Tantalum  |
| Style:              | SMD Chip   |
| Description:        | SMD, Molded, Low ESR, Surge Robust                       |
| Features:           | Low ESR, Surge Robust                                    |
| RoHS:               | Yes  |
| Termination:        | Tin  |
| Notes:              | Obsolete. Old Part Number [Obsolete] Was B45004E4779M606 |

| Dimensions |                |
|------------|----------------|
| Footprint  | 7343           |
| L          | 7.3mm +/-0.3mm |
| W          | 4.3mm +/-0.3mm |
| H          | 4.1mm +/-0.3mm |
| S          | 1.3mm +/-0.3mm |
| F          | 2.4mm +/-0.1mm |
| K          | 1.8mm TYP      |

| Packaging Specifications |            |
|--------------------------|------------|
| Packaging:               | T&R, 178mm |
| Packaging Quantity:      | 400        |

| Specifications         |  |
|------------------------|--|
| Capacitance:           | 470 uF   |
| Capacitance Tolerance: | 20%  |
| Voltage DC:            | 4 VDC (85C), 2.68 VDC (125C)                         |
| Temperature Range:     | -55/+125C  |
| Rated Temperature:     | 85C  |
| Dissipation Factor:    | 8%   |
| Failure Rate:          | N/A  |
| Resistance:            | 0.06 Ohms (100kHz)                                   |
| Current:               | 1660 mAmps (25C), 1494 mAmps (85C), 664 mAmps (125C) |
| Leakage Current:       | 18.8 uA  |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.